



NSAI
Standards

Irish Standard
I.S. EN 61788-17:2013

Superconductivity -- Part 17: Electronic characteristic measurements - Local critical current density and its distribution in large-area superconducting films (IEC 61788-17:2013 (EQV))

I.S. EN 61788-17:2013

Incorporating amendments/corrigenda issued since publication:

The National Standards Authority of Ireland (NSAI) produces the following categories of formal documents:

I.S. xxx: Irish Standard – national specification based on the consensus of an expert panel and subject to public consultation.

S.R. xxx: Standard Recommendation - recommendation based on the consensus of an expert panel and subject to public consultation.

SWiFT xxx: A rapidly developed recommendatory document based on the consensus of the participants of an NSAI workshop.

<i>This document replaces:</i>	<i>This document is based on:</i> EN 61788-17:2013	<i>Published:</i> 5 April, 2013
This document was published under the authority of the NSAI and comes into effect on: 24 April, 2013		ICS number: 17.220.20 29.050
NSAI 1 Swift Square, Northwood, Santry Dublin 9	T +353 1 807 3800 F +353 1 807 3838 E standards@nsai.ie W NSAI.ie	Sales: T +353 1 857 6730 F +353 1 857 6729 W standards.ie
Údarás um Chaighdeáin Náisiúnta na hÉireann		

EUROPEAN STANDARD
NORME EUROPÉENNE
EUROPÄISCHE NORM

EN 61788-17

April 2013

ICS 17.220.20; 29.050

English version

**Superconductivity -
Part 17: Electronic characteristic measurements -
Local critical current density and its distribution in large-area
superconducting films
(IEC 61788-17:2013)**

Supraconductivité -
Partie 17: Mesures de caractéristiques
électroniques -
Densité de courant critique local et sa
distribution dans les films
supraconducteurs de grande surface
(CEI 61788-17:2013)

Supraleitfähigkeit -
Teil 17: Messungen der elektronischen
Charakteristik -
Lokale kritische Stromdichte und deren
Verteilung in großflächigen supraleitenden
Schichten
(IEC 61788-17:2013)

This European Standard was approved by CENELEC on 2013-02-20. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, Former Yugoslav Republic of Macedonia, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and the United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

Management Centre: Avenue Marnix 17, B - 1000 Brussels

Foreword

The text of document 90/310/FDIS, future edition 1 of IEC 61788-17, prepared by IEC TC 90, "Superconductivity" was submitted to the IEC-CENELEC parallel vote and approved by CENELEC as EN 61788-17:2013.

The following dates are fixed:

- latest date by which the document has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2013-11-20
- latest date by which the national standards conflicting with the document have to be withdrawn (dow) 2016-02-20

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC [and/or CEN] shall not be held responsible for identifying any or all such patent rights.

Endorsement notice

The text of the International Standard IEC 61788-17:2013 was approved by CENELEC as a European Standard without any modification.

Annex ZA

(normative)

Normative references to international publications with their corresponding European publications

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE When an international publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60050	Series	International electrotechnical vocabulary	-	-

This page is intentionally left BLANK.

CONTENTS

FOREWORD.....	4
INTRODUCTION.....	6
1 Scope.....	8
2 Normative reference.....	8
3 Terms and definitions.....	8
4 Requirements.....	9
5 Apparatus.....	9
5.1 Measurement equipment.....	9
5.2 Components for inductive measurements.....	10
5.2.1 Coils.....	10
5.2.2 Spacer film.....	11
5.2.3 Mechanism for the set-up of the coil.....	11
5.2.4 Calibration wafer.....	11
6 Measurement procedure.....	12
6.1 General.....	12
6.2 Determination of the experimental coil coefficient.....	12
6.2.1 Calculation of the theoretical coil coefficient k	12
6.2.2 Transport measurements of bridges in the calibration wafer.....	13
6.2.3 U_3 measurements of the calibration wafer.....	13
6.2.4 Calculation of the E - J characteristics from frequency-dependent I_{th} data.....	13
6.2.5 Determination of the k' from J_{ct} and J_{c0} values for an appropriate E	14
6.3 Measurement of J_c in sample films.....	15
6.4 Measurement of J_c with only one frequency.....	15
6.5 Examples of the theoretical and experimental coil coefficients.....	16
7 Uncertainty in the test method.....	17
7.1 Major sources of systematic effects that affect the U_3 measurement.....	17
7.2 Effect of deviation from the prescribed value in the coil-to-film distance.....	18
7.3 Uncertainty of the experimental coil coefficient and the obtained J_c	18
7.4 Effects of the film edge.....	19
7.5 Specimen protection.....	19
8 Test report.....	19
8.1 Identification of test specimen.....	19
8.2 Report of J_c values.....	19
8.3 Report of test conditions.....	19
Annex A (informative) Additional information relating to Clauses 1 to 8.....	20
Annex B (informative) Optional measurement systems.....	26
Annex C (informative) Uncertainty considerations.....	32
Annex D (informative) Evaluation of the uncertainty.....	37
Bibliography.....	43
Figure 1 – Diagram for an electric circuit used for inductive J_c measurement of HTS films.....	10
Figure 2 – Illustration showing techniques to press the sample coil to HTS films.....	11
Figure 3 – Example of a calibration wafer used to determine the coil coefficient.....	12

Figure 4 – Illustration for the sample coil and the magnetic field during measurement.....	13
Figure 5 – E - J characteristics measured by a transport method and the U_3 inductive method	14
Figure 6 –Example of the normalized third-harmonic voltages (U_3/fI_0) measured with various frequencies.....	15
Figure 7 – Illustration for coils 1 and 3 in Table 1	16
Figure 8 – The coil-factor function $F(r) = 2H_0/I_0$ calculated for the three coils.....	17
Figure 9 – The coil-to-film distance Z_1 dependence of the theoretical coil coefficient k	18
Figure A.1 – Illustration for the sample coil and the magnetic field during measurement	22
Figure A.2 – (a) U_3 and (b) U_3/I_0 plotted against I_0 in a YBCO thin film measured in applied DC magnetic fields, and the scaling observed when normalized by I_{th} (insets).....	23
Figure B.1 – Schematic diagram for the variable-RL-cancel circuit	27
Figure B.2 – Diagram for an electrical circuit used for the 2-coil method	27
Figure B.3 – Harmonic noises arising from the power source	28
Figure B.4 – Noise reduction using a cancel coil with a superconducting film	28
Figure B.5 – Normalized harmonic noises (U_3/fI_0) arising from the power source	29
Figure B.6 – Normalized noise voltages after the reduction using a cancel coil with a superconducting film	29
Figure B.7 – Normalized noise voltages after the reduction using a cancel coil without a superconducting film	30
Figure B.8 – Normalized noise voltages with the 2-coil system shown in Figure B.2.....	30
Figure D.1 – Effect of the coil position against a superconducting thin film on the measured J_c values	41
Table 1 – Specifications and coil coefficients of typical sample coils	16
Table C.1 – Output signals from two nominally identical extensometers	33
Table C.2 – Mean values of two output signals	33
Table C.3 – Experimental standard deviations of two output signals	33
Table C.4 – Standard uncertainties of two output signals	34
Table C.5 – Coefficient of variations of two output signals	34
Table D.1 – Uncertainty budget table for the experimental coil coefficient k'	37
Table D.2 – Examples of repeated measurements of J_c and n -values	40

INTERNATIONAL ELECTROTECHNICAL COMMISSION

SUPERCONDUCTIVITY –**Part 17: Electronic characteristic measurements –
Local critical current density and its distribution
in large-area superconducting films**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.

International Standard IEC 61788-17 has been prepared by IEC technical committee 90: Superconductivity.

The text of this standard is based on the following documents:

FDIS	Report on voting
90/310/FDIS	90/319/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all the parts of the IEC 61788 series, published under the general title *Superconductivity*, can be found on the IEC website.

I.S. EN 61788-17:2013

61788-17 © IEC:2013

– 5 –

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

Over twenty years after their discovery in 1986, high-temperature superconductors are now finding their way into products and technologies that will revolutionize information transmission, transportation, and energy. Among them, high-temperature superconducting (HTS) microwave filters, which exploit the extremely low surface resistance of superconductors, have already been commercialized. They have two major advantages over conventional non-superconducting filters, namely: low insertion loss (low noise characteristics) and high frequency selectivity (sharp cut) [1]¹. These advantages enable a reduced number of base stations, improved speech quality, more efficient use of frequency bandwidths, and reduced unnecessary radio wave noise.

Large-area superconducting thin films have been developed for use in microwave devices [2]. They are also used for emerging superconducting power devices, such as, resistive-type superconducting fault-current limiters (SFCLs) [3–5], superconducting fault detectors used for superconductor-triggered fault current limiters [6, 7] and persistent-current switches used for persistent-current HTS magnets [8, 9]. The critical current density J_c is one of the key parameters that describe the quality of large-area HTS films. Nondestructive, AC inductive methods are widely used to measure J_c and its distribution for large-area HTS films [10–13], among which the method utilizing third-harmonic voltages $U_3 \cos(3\omega t + \theta)$ is the most popular [10, 11], where ω , t and θ denote the angular frequency, time, and initial phase, respectively. However, these conventional methods are not accurate because they have not considered the electric-field E criterion of the J_c measurement [14, 15] and sometimes use an inappropriate criterion to determine the threshold current I_{th} from which J_c is calculated [16]. A conventional method can obtain J_c values that differ from the accurate values by 10 % to 20 % [15]. It is thus necessary to establish standard test methods to precisely measure the local critical current density and its distribution, to which all involved in the HTS filter industry can refer for quality control of the HTS films. Background knowledge on the inductive J_c measurements of HTS thin films is summarized in Annex A.

In these inductive methods, AC magnetic fields are generated with AC currents $I_0 \cos \omega t$ in a small coil mounted just above the film, and J_c is calculated from the threshold coil current I_{th} , at which full penetration of the magnetic field to the film is achieved [17]. For the inductive method using third-harmonic voltages U_3 , U_3 is measured as a function of I_0 , and the I_{th} is determined as the coil current I_0 at which U_3 starts to emerge. The induced electric fields E in the superconducting film at $I_0 = I_{th}$, which are proportional to the frequency f of the AC current, can be estimated by a simple Bean model [14]. A standard method has been proposed to precisely measure J_c with an electric-field criterion by detecting U_3 and obtaining the n -value (index of the power-law E - J characteristics) by measuring I_{th} precisely at various frequencies [14, 15, 18, 19]. This method not only obtains precise J_c values, but also facilitates the detection of degraded parts in inhomogeneous specimens, because the decline of n -value is more remarkable than the decrease of J_c in such parts [15]. It is noted that this standard method is excellent for assessing homogeneity in large-area HTS films, although the relevant parameter for designing microwave devices is not J_c , but the surface resistance. For application of large-area superconducting thin films to SFCLs, knowledge on J_c distribution is vital, because J_c distribution significantly affects quench distribution in SFCLs during faults.

The International Electrotechnical Commission (IEC) draws attention to the fact that it is claimed that compliance with this document may involve the use of a patent concerning the determination of the E - J characteristics by inductive J_c measurements as a function of frequency, given in the Introduction, Clause 1, Clause 4 and 5.1.

IEC takes no position concerning the evidence, validity and scope of this patent right.

The holder of this patent right has assured the IEC that he is willing to negotiate licenses free of charge with applicants throughout the world. In this respect, the statement of the holder of this patent right is registered with the IEC. Information may be obtained from:

¹ Numbers in square brackets refer to the Bibliography.

I.S. EN 61788-17:2013

61788-17 © IEC:2013

– 7 –

Name of holder of patent right:

National Institute of Advanced Industrial Science and Technology

Address:

Intellectual Property Planning Office, Intellectual Property Department

1-1-1, Umezono, Tsukuba, Ibaraki Prefecture, Japan

Attention is drawn to the possibility that some of the elements of this document may be subject to patent rights other than those identified above. IEC shall not be held responsible for identifying any or all such patent rights.

ISO (www.iso.org/patents) and IEC (<http://patents.iec.ch>) maintain on-line data bases of patents relevant to their standards. Users are encouraged to consult the data bases for the most up to date information concerning patents.

SUPERCONDUCTIVITY –

Part 17: Electronic characteristic measurements – Local critical current density and its distribution in large-area superconducting films

1 Scope

This part of IEC 61788 describes the measurements of the local critical current density (J_c) and its distribution in large-area high-temperature superconducting (HTS) films by an inductive method using third-harmonic voltages. The most important consideration for precise measurements is to determine J_c at liquid nitrogen temperatures by an electric-field criterion and obtain current-voltage characteristics from its frequency dependence. Although it is possible to measure J_c in applied DC magnetic fields [20, 21]², the scope of this standard is limited to the measurement without DC magnetic fields.

This technique intrinsically measures the critical sheet current that is the product of J_c and the film thickness d . The range and measurement resolution for $J_c d$ of HTS films are as follows:

- $J_c d$: from 200 A/m to 32 kA/m (based on results, not limitation);
- Measurement resolution: 100 A/m (based on results, not limitation).

2 Normative reference

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050 (all parts), *International Electrotechnical Vocabulary* (available at <<http://www.electropedia.org>>)

3 Terms and definitions

For the purposes of this document, the definitions given in IEC 60050-815:2000, some of which are repeated here for convenience, apply.

3.1 critical current

I_c

maximum direct current that can be regarded as flowing without resistance

Note 1 to entry: I_c is a function of magnetic field strength and temperature.

[SOURCE: IEC 60050-815:2000, 815-03-01]

² Numbers in square brackets refer to the Bibliography.

This is a free preview. Purchase the entire publication at the link below:

[Product Page](#)

-
- Looking for additional Standards? Visit Intertek Inform Infostore
 - Learn about LexConnect, All Jurisdictions, Standards referenced in Australian legislation
-