



NSAI
Standards

Irish Standard
I.S. EN 62271-106:2011

High-voltage switchgear and
controlgear -- Part 106: Alternating
current contactors, contactor-based
controllers and motor-starters (IEC
62271-106:2011 (EQV))

I.S. EN 62271-106:2011

Incorporating amendments/corrigenda issued since publication:

The National Standards Authority of Ireland (NSAI) produces the following categories of formal documents:

I.S. xxx: Irish Standard – national specification based on the consensus of an expert panel and subject to public consultation.

S.R. xxx: Standard Recommendation - recommendation based on the consensus of an expert panel and subject to public consultation.

SWiFT xxx: A rapidly developed recommendatory document based on the consensus of the participants of an NSAI workshop.

<i>This document replaces:</i> EN 60470:2000	<i>This document is based on:</i> EN 62271-106:2011 EN 60470:2000	<i>Published:</i> 7 October, 2011 16 May, 2000
This document was published under the authority of the NSAI and comes into effect on: 14 October, 2011		ICS number: 29.130.10
NSAI 1 Swift Square, Northwood, Santry Dublin 9	T +353 1 807 3800 F +353 1 807 3838 E standards@nsai.ie W NSAI.ie	Sales: T +353 1 857 6730 F +353 1 857 6729 W standards.ie
Údarás um Chaighdeáin Náisiúnta na hÉireann		

EUROPEAN STANDARD

EN 62271-106

NORME EUROPÉENNE

October 2011

EUROPÄISCHE NORM

ICS 29.130.10

Supersedes EN 60470:2000 + corr. Jun.2000

English version

**High-voltage switchgear and controlgear -
Part 106: Alternating current contactors, contactor-based controllers and
motor-starters
(IEC 62271-106:2011)**

Appareillage à haute tension -
Partie 106: Contacteurs, combinés de
démarrage à contacteurs et démarreurs
de moteurs, pour courant alternatif
(CEI 62271-106:2011)

Hochspannungs-Schaltgeräte und -
Schaltanlagen -
Teil 106: Wechselstrom-Schütze,
Kombinationsstarter und Motorstarter mit
Schützen
(IEC 62271-106:2011)

This European Standard was approved by CENELEC on 2011-09-23. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland and the United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

Management Centre: Avenue Marnix 17, B - 1000 Brussels

Foreword

The text of document 17A/971/FDIS, future edition 1 of IEC 62271-106, prepared by SC 17A, "High-voltage switchgear and controlgear", of IEC TC 17, "Switchgear and controlgear" was submitted to the IEC-CENELEC parallel vote and approved by CENELEC as EN 62271-106:2011.

The following dates are fixed:

- latest date by which the document has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2012-06-23
- latest date by which the national standards conflicting with the document have to be withdrawn (dow) 2014-09-23

This document supersedes EN 60470:2000 + corrigendum June 2000.

EN 62271-106:2011 includes the following significant technical changes with respect to EN 60470:2000:

- Scope and object: The voltage range covered by the standard was expanded from 12 Kv to 24 kV. Overload relay calibration and testing is not covered by this standard.
- 3 Terms and definitions: Added definitions for capacitor switching classes.
- 4.1 Rated voltage: Added 15, 17,5 and 24 kV as standard voltage values.
- 4.109.2 Starting duty of reduced-voltage starters: Added ratings for autotransformer and reactor starters (was in the testing section).
- 4.112 Rated capacitive switching currents: Added capacitor switching current ratings.
- 5.101 Protective relays: Removed the requirements for overload relays. This section is obsolete since there are only a few MV starters fitted with thermal overload relays and electronic relays have their own standards.
- 6.2.5 Application of the test voltage and test conditions (former 6.2.2 b)): Changed wording of requirement for impulse across the open gap of vacuum contactors.
- 6.4.2 Auxiliary circuits: The requirement for resistance checks of auxiliary circuits was deleted.
- 6.5.5.104 Temperature rise of the auto-transformer or reactor for two-step auto-transformer or reactor starters: Reworded to transfer ratings to subclause 4.109.2.
- 6.102.9 Condition following making and breaking tests: Gave specific direction as to what the tolerance should be based on where the resistance was to be checked.
- 6.104 Short-circuit current making and breaking tests: Clarified test conditions for shortcircuit testing.
- 6.109 Capacitive current switching tests: Added capacitive current switching tests.
- Annex B: Added Table B.1 – Tolerances on test quantities for type test.

This standard is to be read in conjunction with EN 62271-1:2008, to which it refers and which is applicable unless otherwise specified in this standard. In order to simplify the indication of corresponding requirements, the same numbering of clauses and subclauses is used as in EN 62271-1. Amendments to these clauses and subclauses are given under the same references whilst additional subclauses are numbered from 101.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC [and/or CEN] shall not be held responsible for identifying any or all such patent rights.

Endorsement notice

The text of the International Standard IEC 62271-106:2011 was approved by CENELEC as a European Standard without any modification.

In the official version, for Bibliography, the following notes have to be added for the standards indicated:

IEC 60034-11	NOTE	Harmonized as EN 60034-11.
IEC 60060 series	NOTE	Harmonized in EN 60060 series.
IEC 60060-1	NOTE	Harmonized as EN 60060-1.
IEC 60060-2	NOTE	Harmonized as EN 60060-2.
IEC 60076-11:2004	NOTE	Harmonized as EN 60076-11:2004 (not modified).
IEC 60076-2	NOTE	Harmonized as EN 60076-2.
IEC 60255-8	NOTE	Harmonized as EN 60255-8.
IEC 60947-5-1	NOTE	Harmonized as EN 60947-5-1.
IEC 61230	NOTE	Harmonized as EN 61230.
IEC 61812-1	NOTE	Harmonized as EN 61812-1.
IEC 62271-103	NOTE	Harmonized as EN 62271-103.
IEC 62271-110:2009	NOTE	Harmonized as EN 62271-110:2009 (not modified).

Annex ZA (normative)

Normative references to international publications with their corresponding European publications

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE When an international publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60282-1	-	High-voltage fuses - Part 1: Current-limiting fuses	EN 60282-1	-
IEC 60417	Data- base	Graphical symbols for use on equipment	-	-
IEC 60644	-	Specification for high voltage fuse-links for motor circuit application	EN 60644	-
IEC 62271-1	2007	High-voltage switchgear and controlgear - Part 1: Common specifications	EN 62271-1	2008
IEC 62271-100	2008	High-voltage switchgear and controlgear - Part 100: Alternating current circuit-breakers	EN 62271-100	2009
IEC 62271-102	-	High-voltage switchgear and controlgear - Part 102: Alternating current disconnectors and earthing switches	EN 62271-102	-
IEC 62271-200	2003	High-voltage switchgear and controlgear - Part 200: AC metal-enclosed switchgear and controlgear for rated voltages above 1 kV and up to and including 52 kV	EN 62271-200	2004

CONTENTS

FOREWORD.....	3
1 General	5
2 Normal and special service conditions	7
3 Terms and definitions	7
4 Ratings.....	19
5 Design and construction	32
6 Type tests	36
7 Routine tests	57
8 Guide to the selection of contactors and motor-starters for service.....	58
9 Information to be given with enquiries, tenders and orders	62
10 Transport, storage, installation, operation and maintenance	63
11 Safety.....	63
Annex A (normative) Records and reports of type tests for making, breaking and short-time current performance	70
Annex B (normative) Tolerances	73
Annex C (informative) List of symbols and abbreviations	79
Bibliography.....	80
Figure 1 – Examples of speed/time curves.....	64
Figure 2 – Test duties A and B – preferred earth point	65
Figure 3 – Test duties A and B – alternative earth point.....	65
Figure 4 – Test duty C – preferred earth point.....	66
Figure 5 – Test duty C – alternative earth point.....	66
Figure 6 – Representation by two parameters of a prospective TRV of a circuit	67
Figure 7 – Representation of the specified TRV by a two-parameter reference line and a delay line	67
Figure 8 – Determination of power frequency recovery voltage	68
Figure 9 – Characteristics for determining take-over current	69
Table 1 – Ratings and characteristics	20
Table 2 – Utilization categories	26
Table 3 – Characteristics dependent on starter type	31
Table 4 – Applicable type tests	37
Table 5 – Intermittent duty operating cycles.....	40
Table 6 – Verification of rated making and breaking capacities – Conditions for making and breaking corresponding to the several utilization categories at rated voltage U_f	44
Table 7 – Relationship between current broken I_C and OFF time	47
Table 8 – Overload current withstand requirements	48
Table 9 – Transient recovery voltage characteristics.....	53
Table 10 – Verification of the number of on-load operating cycles – Conditions for making and breaking corresponding to the several utilization categories.....	55
Table B.1 – Tolerances on test quantities for type test.....	73

INTERNATIONAL ELECTROTECHNICAL COMMISSION

HIGH-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

**Part 106: Alternating current contactors,
contactor-based controllers and motor-starters**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62271-106 has been prepared by subcommittee 17A: High-voltage switchgear and controlgear, of IEC technical committee 17: Switchgear and controlgear.

This standard cancels and replaces the second edition of IEC 60470 published in 1999. It constitutes a technical revision.

This edition includes the following significant technical changes with respect to IEC 60470:1999:

- **Scope and object:** The voltage range covered by the standard was expanded from 12 kV to 24 kV. Overload relay calibration and testing is not covered by this standard.
- **3 Terms and definitions:** Added definitions for capacitor switching classes.
- **4.1 Rated voltage:** Added 15, 17,5 and 24 kV as standard voltage values.
- **4.109.2 Starting duty of reduced-voltage starters:** Added ratings for autotransformer and reactor starters (was in the testing section).

- 4.112 Rated capacitive switching currents: Added capacitor switching current ratings.
- 5.101 Protective relays: Removed the requirements for overload relays. This section is obsolete since there are only a few MV starters fitted with thermal overload relays and electronic relays have their own standards.
- 6.2.5 Application of the test voltage and test conditions (former 6.2.2 b)): Changed wording of requirement for impulse across the open gap of vacuum contactors.
- 6.4.2 Auxiliary circuits: The requirement for resistance checks of auxiliary circuits was deleted.
- 6.5.5.104 Temperature rise of the auto-transformer or reactor for two-step auto-transformer or reactor starters: Reworded to transfer ratings to subclause 4.109.2.
- 6.102.9 Condition following making and breaking tests: Gave specific direction as to what the tolerance should be based on where the resistance was to be checked.
- 6.104 Short-circuit current making and breaking tests: Clarified test conditions for short-circuit testing.
- 6.109 Capacitive current switching tests: Added capacitive current switching tests.
- Annex B: Added Table B.1 – Tolerances on test quantities for type test.

This standard is to be read in conjunction with IEC 62271-1:2007, to which it refers and which is applicable unless otherwise specified in this standard. In order to simplify the indication of corresponding requirements, the same numbering of clauses and subclauses is used as in IEC 62271-1. Amendments to these clauses and subclauses are given under the same references whilst additional subclauses are numbered from 101.

The text of this standard is based on the following documents:

FDIS	Report on voting
17A/971/FDIS	17A/976/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The list of all parts of the IEC 62271 series under the general title, *High-voltage switchgear and controlgear*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

HIGH-VOLTAGE SWITCHGEAR AND CONTROLGEAR –

Part 106: Alternating current contactors, contactor-based controllers and motor-starters

1 General

1.1 Scope and object

This part of IEC 62271 is applicable to a.c. contactors and/or contactor-based controllers and motor-starters designed for indoor installation and operation at frequencies up to and including 60 Hz on systems having voltages above 1 000 V but not exceeding 24 000 V.

It is applicable only to three-pole devices for use in three-phase systems, and single-pole devices for use in single-phase systems. Two-pole contactors and starters for use in single-phase systems are subject to agreement between manufacturer and user.

Contactors and/or starters dealt with in this standard typically do not have adequate short-circuit interruption capability. In this context, this standard gives requirements for

- motor starters associated with separate short-circuit protective devices;
- controllers - contactors combined with short-circuit protective devices (SCPD).

Contactors intended for closing and opening electric circuits and, if combined with suitable relays, for protecting these circuits against operating overloads are covered in this standard.

This standard is also applicable to the operating devices of contactors and to their auxiliary equipment.

Motor-starters intended to start and accelerate motors to normal speed, to ensure continuous operation of motors, to switch off the supply from the motor and to provide means for the protection of motors and associated circuits against operating overloads are dealt with.

Motor-starter types included are

- direct-on-line starters;
- reversing starters;
- two-direction starters;
- reduced kVA (voltage) starters;
 - auto-transformer starters;
 - rheostatic starters;
 - reactor starters.

This standard does not apply to

- circuit-breaker-based motor-starters;
- single-pole operation of multi-pole contactors or starters;
- two-step auto-transformer starters designed for continuous operation in the starting position;
- unbalanced rheostatic rotor starters, i.e. where the resistances do not have the same value in all phases;

- equipment designed not only for starting, but also for adjustment of speed;
- liquid starters and those of the "liquid-vapour" type;
- semiconductor contactors and starters making use of semiconductor contactors in the main circuit;
- rheostatic stator starters;
- contactors or starters designed for special applications.

This standard does not deal with components contained in contactors and contactor-based motor-starters, for which individual specifications exist.

NOTE 1 Thermal electrical relays are covered by IEC 60255-8.

NOTE 2 High-voltage current-limiting fuses are covered by IEC 60282-1 and IEC 60644.

NOTE 3 Metal-enclosed switchgear and controlgear for rated voltages above 1 kV and up to and including 52 kV are covered by IEC 62271-200.

NOTE 4 Disconnectors and earthing switches are covered by IEC 62271-102.

NOTE 5 High-voltage switches above 1 kV and less than 52 kV are covered by IEC 62271-103¹.

The object of this standard is to state

- a) the characteristics of contactors and starters and associated equipment;
- b) the conditions with which contactors or starters shall comply with reference to:
 - 1) their operation and behaviour,
 - 2) their dielectric properties,
 - 3) the degrees of protection provided by their enclosures, where applicable,
 - 4) their construction,
 - 5) for controllers, interactions between the various components, for example SCPD co-ordination;
- c) the tests intended for confirming that these conditions have been met, and the methods to be adopted for these tests;
- d) the information to be given with the equipment or in the manufacturer's literature.

1.2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60282-1, *High-voltage fuses – Part 1: Current-limiting fuses*

IEC 60417, *Graphical symbols for use on equipment*

IEC 60644, *Specification for high-voltage fuse-links for motor circuit applications*

IEC 62271-1:2007, *High-voltage switchgear and controlgear – Part 1: Common specifications*

IEC 62271-100:2008, *High-voltage switchgear and controlgear – Part 100: Alternating-current circuit-breakers*

¹ To be published

This is a free preview. Purchase the entire publication at the link below:

[Product Page](#)

-
- [Looking for additional Standards? Visit Intertek Inform Infostore](#)
 - [Learn about LexConnect, All Jurisdictions, Standards referenced in Australian legislation](#)
-