



NSAI
Standards

Irish Standard
I.S. EN 50628:2016

Erection of electrical installations in underground mines

I.S. EN 50628:2016

Incorporating amendments/corrigenda/National Annexes issued since publication:

The National Standards Authority of Ireland (NSAI) produces the following categories of formal documents:

I.S. xxx: Irish Standard — national specification based on the consensus of an expert panel and subject to public consultation.

S.R. xxx: Standard Recommendation — recommendation based on the consensus of an expert panel and subject to public consultation.

SWiFT xxx: A rapidly developed recommendatory document based on the consensus of the participants of an NSAI workshop.

This document replaces/revises/consolidates the NSAI adoption of the document(s) indicated on the CEN/CENELEC cover/Foreword and the following National document(s):

NOTE: The date of any NSAI previous adoption may not match the date of its original CEN/CENELEC document.

This document is based on:

EN 50628:2016

Published:

2016-07-01

This document was published under the authority of the NSAI and comes into effect on:

2016-07-19

ICS number:

NOTE: If blank see CEN/CENELEC cover page

NSAI
1 Swift Square,
Northwood, Santry
Dublin 9

T +353 1 807 3800
F +353 1 807 3838
E standards@nsai.ie
W NSAI.ie

Sales:
T +353 1 857 6730
F +353 1 857 6729
W standards.ie

Údarás um Chaighdeáin Náisiúnta na hÉireann

National Foreword

I.S. EN 50628:2016 is the adopted Irish version of the European Document EN 50628:2016, Erection of electrical installations in underground mines

This document does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

Compliance with this document does not of itself confer immunity from legal obligations.

In line with international standards practice the decimal point is shown as a comma (,) throughout this document.

This page is intentionally left blank

EUROPEAN STANDARD

EN 50628

NORME EUROPÉENNE

EUROPÄISCHE NORM

July 2016

ICS 29.260.20

English Version

Erection of electrical installations in underground mines

Construction des installations électriques dans les mines
souterraines

Errichten elektrischer Anlagen im Bergbau unter Tage

This European Standard was approved by CENELEC on 2016-05-23. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, Former Yugoslav Republic of Macedonia, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and the United Kingdom.



European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

CEN-CENELEC Management Centre: Avenue Marnix 17, B-1000 Brussels

Contents

Page

European foreword	5
Introduction	6
1 Scope	7
2 Normative references	8
3 Terms and definitions	9
4 General.....	21
4.1 General requirements.....	21
4.2 Initial inspections.....	22
4.3 Competence of personnel.....	22
4.4 Documentation.....	22
5 Means of protection against electric- and electrostatic charging	23
6 Rooms and Locations	23
6.1 Electrical service rooms	23
6.2 Closed electrical service rooms.....	23
6.3 Other rooms	23
7 Protection against fire spreading.....	24
7.1 General requirements.....	24
8 Insulation, Insulation-resistance and its check.....	24
8.1 Insulation	24
8.2 Value of insulation resistance	25
8.3 Insulation resistance check.....	25
9 Signboards, labels, wiring diagrams, inscriptions.....	26
9.1 General requirements.....	26
10 Nominal voltages	26
10.1 General requirements.....	26
10.2 Voltage ranges	27
11 Protection against electrical shock	27
11.1 Requirements for basic protection	27
11.1.1 Protection by basic insulation of live parts	27
11.1.2 Protection by barriers or enclosures.....	27
11.1.3 Protection by obstacles and placing out of reach	28
11.2 Requirements for fault protection.....	28
12 Protection in IT-Systems.....	28
12.1 General.....	28
12.2 Earth fault detection in IT-systems	29
12.3 Design of IT system	29
12.4 Insulation monitoring	30
12.5 Protective conductor.....	31
12.6 Electrical protection devices in IT-systems.....	33
12.7 Design of cables being monitored by a protection device.....	36
13 Protection in TN-systems	37

13.1	TN-S- systems with residual current devices (RCD)	37
13.2	TN-S System without residual current devices (RCD).....	38
14	Other means of protection	38
15	Protection against danger caused by mechanical influence on non-intrinsically safe cables.....	38
15.1	General requirements	38
15.2	Cables to supply mobile electrical equipment	39
15.3	Cable in areas of mining activities or road heading areas till 50 m far from the road heading face.....	40
16	Intrinsically safe electrical systems	40
16.1	General requirements for selection.....	40
16.2	Descriptive system document	40
16.3	Erection	40
16.4	Separation of intrinsically and non-intrinsically safe circuits	41
16.5	Separation of different intrinsically safe circuits	42
16.6	Earthing	42
16.7	Cable for intrinsically safe systems	42
17	Installation of transformers	42
18	Substations	42
19	Disconnecting devices in line of each switch-gears	43
20	Switchgears	43
21	Couplers and connectors	43
21.1	General requirements for use of couplers and connectors	43
21.2	Additional requirements using couplers	43
22	Luminaries and lighting installation	44
23	Cables	44
23.1	Design of cables	44
23.2	Conductor materials.....	45
23.3	Current carrying capacity.....	45
23.4	Coverings and outer protective covers.....	45
23.5	Different circuits within one cable	46
23.6	Laying out of cables	46
23.7	Glanding, terminating or making off	47
23.8	Laying out of non-insulated conductors.....	48
23.9	Additional requirements for the use of single core cable	49
24	Protection of electrical equipment or installation against overcurrent.....	49
24.1	Overcurrent protection devices	49
24.2	Overload protection	50
24.3	Short circuit protection.....	50
24.4	Minimum short circuit current	51
25	Calculation of short circuit currents	52
26	Additional requirements for systems and equipment with nominal voltage of more than 1 kV up to 6,6 kV in production areas and road heading	52
26.1	General requirements	52
26.2	Switchgears	52
26.3	Test of insulation resistance of non-alive cable in production areas and road headings	52
26.4	Insulation monitoring of alive systems.....	53
26.5	Earth protection in IT systems.....	53
26.6	Monitoring of non-alive systems	53
26.7	Electrical protection devices for feeding cables of electrical equipment	54

EN 50628:2016

26.8	Cable design.....	54
27	Additional requirements for cable entry selection.....	54
	Annex A (informative) Documentation	55
	Annex B (normative) Tables and figures regarding free space	56
	Annex C (informative) Example for a galvanically separated system (in production areas or road headings)	58
	Annex D (informative) Example for calculation (according to 12.3.6).....	61
D.1	General.....	61
D.2	Legend	61
D.3	Necessary system parameters	61
D.4	Determination of the reference points of the system	61
D.5	Calculation of the capacitive earth fault current and displaying in a figure (see Figure D.2)	62
D.6	Overlay of capacitive and inductive earth fault current $I_{eL} - I_{eC} = I_{eB}$	62
D.7	Calculation of the voltage drop caused by the wattles component of the earth fault current.....	63
D.8	Calculation of the voltage drop caused by the active component of the earth fault current	64
D.9	Resulting voltage drop U_F by geometrical addition	64
	Annex E (informative) Table for cables suitable for underground workings	66
	Annex F (informative) Table for current carrying capacity of cables suitable for underground workings	73
	Bibliography	76

European foreword

This document (EN 50628:2016) has been prepared by CLC/TC 31 “Electrical apparatus for potentially explosive atmospheres”.

The following dates are fixed:

- latest date by which this document has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2017-05-23
- latest date by which the national standards conflicting with this document have to be withdrawn (dow) 2020-05-23

This document will be read in conjunction with the European Standards for the specific types of protection listed in the EN 60079 series of standards.

This document will also be read in conjunction with EN 1127-2.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC [and/or CEN] shall not be held responsible for identifying any or all such patent rights.

EN 50628:2016

Introduction

When electrical equipment is to be installed in underground workings where an explosive atmosphere is likely to occur, protective measures are applied to avoid the ignition of firedamp either under normal operation of the electrical installation or under fault conditions.

Mines can be either gassy or non-gassy depending upon the mineral/material being extracted and whether or not firedamp can occur in the workings. It is usual practice to consider all coal mines as gassy mines. Non-coal mines can however, also be susceptible to the occurrence of firedamp e.g. if they are mining minerals/materials in the vicinity of oil bearing strata or unworked coal seams which are to be disturbed by the mining process, or are susceptible to outbursts of flammable gas.

Due to the fact that in underground workings firedamp is one of the major mining hazards that is to be considered all pieces of electrical equipment need to be selected with regard to this hazard. If there are other significant explosive atmospheres than firedamp the hazard occurring from these explosive atmospheres needs to be taken into account.

Directive 2014/34/EU extends the definition of potentially explosive atmosphere to include combustible dust as well as firedamp. Extensive research¹⁾ has shown that the minimum ignition energy (MIE) of coal dust/ air mixture is several hundred times higher than that of a firedamp/ air mixture and that the maximum experimental safe gap (MESG) for coal dust particles is more than double that for firedamp. It is therefore reasonable to assume that equipment, protective systems and components that are designed, constructed and maintained for use in firedamp/ air mixtures are also suitable for use in coal dust/ air mixtures.

Unlike Group II it will be assumed that in Group I industry nearly all underground workings need to be assessed where an explosive atmosphere is likely to occur and classified accordingly as hazardous areas. A zone classification for such underground workings is not possible because the degree of exposure of such an underground working does not depend on local parameters but on time parameters. In accordance with 2014/34/EU (ATEX-Directive) the exposure of the installed equipment may change from normally acceptable firedamp concentration in the mine air (hazardous condition 2; M2 equipment sufficient) to elevated methane concentration (hazardous condition 1; M1 equipment required, M2 equipment to be de-energized) and vice versa.

Areas of a coal mine could be non-hazardous according to national regulations. In such areas equipment that is not ATEX approved may be used, too subject to the risk assessment and specific local rules where national regulations require.

In non-gassy mines it can be possible that in certain regions in the underground workings explosive atmospheres can occur. In these cases national regulations will apply.

In mines where the atmosphere, in addition to firedamp, may contain significant proportions of other flammable gases than firedamp, the installed Group I equipment complies also with the subdivision of Group II corresponding to the other significant flammable gases.

In any underground working, irrespective of the size, there may be numerous sources of ignition apart from those associated with electrical equipment. Precautions will be necessary to ensure safety from other possible ignition sources, but guidance on this aspect is outside the scope of this standard.

Underground mining activities cause other special problems to the electrical installation as well as those arising from firedamp. Rough environmental conditions evoked by climate – temperature and humidity e.g. – rock pressure caused by depth, geometric dimensions of the underground workings, the winning process itself and other similar circumstances require therefore special specifications to the electrical installation in underground mines.

1) Survey on the use of flameproof enclosures in coal dust and methane atmospheres, G. A. Lunn, SM/97/01.

1 Scope

This European Standard specifies the safety requirements for the erection of new electrical installations.

This European Standard is supplementary to other relevant harmonized standards, for example HD 60364 series and the EN 61936 series as regards electrical installation requirements.

This European Standard also refers to EN 60079-0 and its associated standards for the construction, testing and marking requirements of suitable electrical equipment.

EN 60079-14 gives the specific requirements for design, selection and erection of electrical installations in explosive atmospheres.

NOTE EN 60079-14 can apply to electrical installations in mines where explosive gas atmospheres other than firedamp can be formed and to electrical installations in the surface installation of mines.

This European Standard applies to:

- a) electrical installation in underground workings of mines;
- b) electrical installations and parts of electrical installation above ground, which are directly connected with the underground workings in functional and safety relating matters because of being part of the underground working process:

These are in particular:

- safety and monitoring devices relating to the power distribution of the underground workings,
 - communication system of hoisting and inclined haulage plants,
 - intrinsically safe electrical installations of above ground installation being part of underground workings,
 - remote control systems if they shall fulfil increased requirements relating to functional safety,
 - electrical installation and electrical equipment of ventilation systems and shaft casings above ground being endangered by firedamp of the underground ventilation,
 - firedamp drainage systems;
- c) electrical installation in underground workings outside mining if it is demanded of the competent national authorities.

National regulations of the mining authority shall remain unaffected.

This standard applies to installations at all voltages mentioned in Clause 10.

Requirements above both columns are requirements for all underground workings.

Gassy mines

Requirements within left column are requirements for underground workings in the coal mining industry which could be endangered by firedamp.

Other mines

Requirements within right column are requirements for underground workings of the coal mining industry not likely to be endangered by firedamp and for underground workings of non-coal mining industry.

This is a free preview. Purchase the entire publication at the link below:

[Product Page](#)

-
- [Looking for additional Standards? Visit Intertek Inform Infostore](#)
 - [Learn about LexConnect, All Jurisdictions, Standards referenced in Australian legislation](#)
-