This is a free page sample. Access the full version online.



Standard Recommendation S.R. CLC/TR 50503:2010

Guidelines for the inventory control, management, decontamination and/or disposal of electrical equipment and insulating liquids containing PCBs

 $\ensuremath{\mathbb{C}}$ NSAI 2010 No copying without NSAI permission except as permitted by copyright law.

S.R. CLC/TR 50503:2010

Incorporating amendments/corrigenda issued since publication:

This document replaces:		<i>This document is based on: Publis</i> CLC/TR 50503:2010 5 Feb		<i>ed:</i> Jary, 2010
This document was published under the authority of the NSAI and comes into effect on: 10 March, 2010		ICS number: 29.040.10		
NSAI T +353 1 807 3800 Sales: 1 Swift Square, F +353 1 807 3838 T +353 1 857 Northwood, Santry E standards@nsai.ie F +353 1 857 Dublin 9 W NSAI.ie W standards.		7 6729		
Údarás um Chaighdeáin Náisiúnta na hÉireann				

TECHNICAL REPORT

CLC/TR 50503

RAPPORT TECHNIQUE TECHNISCHER BERICHT

February 2010

ICS 29.040.10

English version

Guidelines for the inventory control, management, decontamination and/or disposal of electrical equipment and insulating liquids containing PCBs

This Technical Report was approved by CENELEC on 2009-12-25.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland and the United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization Comité Européen de Normalisation Electrotechnique Europäisches Komitee für Elektrotechnische Normung

Central Secretariat: Avenue Marnix 17, B - 1000 Brussels

© 2010 CENELEC - All rights of exploitation in any form and by any means reserved worldwide for CENELEC members.

CLC/TR 50503:2010

- 2 -

Foreword

This Technical Report has been prepared by CENELEC BTTF 116-1 "Fluids for electrotechnical applications".

It was circulated for voting in accordance with the Internal Regulations, Part 2, Subclause 11.4.3.3 (simple majority).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CEN and CENELEC shall not be held responsible for identifying any or all such patent rights.

- 3 -

Contents

Intro	ductio	on	5	
1	Scope6			
2	Normative references			
3	Terms and Definitions			
4	Inventory and communication		10	
	4.1	PCBs for inventory purposes	10	
	4.2	Equipment containing PCBs for inventory	.11	
	4.3	Sampling of insulating liquids	12	
	4.4	Analytical determinations of PCBs	12	
	4.5	Communications	12	
5	Labe	lling	13	
	5.1	Labelling of equipment containing PCBs	.13	
	5.2	Labelling of equipments after decontamination	13	
6	Mana	aging safety	14	
	6.1	General prescriptions	14	
	6.2	Personal protection devices	15	
	6.3	Handling and transportation	15	
	6.4	Actions in case of accidents	16	
	6.5	Fires	17	
7	Oper	ation and maintenance	17	
	7.1	General criteria for the evaluation of functional degradation	17	
	7.2	Type of monitoring and frequency	18	
	7.3	Maintenance interventions	21	
	7.4	Field screening tests	22	
	7.5	Maintenance report	22	
	7.6	Qualification of operators	22	
8	Deco	ontamination	23	
	8.1	General requirements	23	
	8.2	General principles	23	
	8.3	Decontamination obligations	24	
	8.4	Decontamination methodologies and techniques for mineral insulating oil	25	
	8.5	Decontamination methodologies and techniques for other insulating liquids	.26	
	8.6	Fulfilment of conditions after the decontamination	26	
	8.7	Qualification of operators	28	
9	End	of use	28	
10	Disp	osal	28	
	10.1	Obligations and prohibitions	28	
	10.2	Methodologies and techniques for the decontamination and disposal of wastes	28	

- 4 -

CLC/TR 50503:2010

Annex A (informative) List of PCBs manufacturers and commercial names	.30
Annex B (informative) Example of test report for PCBs inventory	.33
Annex C (informative) Example of communication forms - Equipment/Container card	.34
Annex D (informative) Example of communication forms - Registration card	.35
Annex E (informative) Example of communication forms - Decontamination/Disposal card	36
Annex F (informative) Example of labels for equipment containing PCBs	.37
Annex G (informative) Labels for decontaminated transformers	.38
Annex H (informative) Equivalent toxicity (TEF) for some typical commercial mixtures of PCBs	.39
Annex I (informative) Aroclor mixtures composition and TEQs	.40
Annex J (informative) Typical PCBs clean up levels for surfaces and soil contamination	1 41

Tables

Table 1 - PCBs family	11
Table 2 - Additional test methods for PCBs insulating liquids of power and transformers	
Table 3- Additional test methods for Askarels insulated equipment	20
Table 4 - Recommended types and frequency of tests and inspection	21
Table 5 – Time deadline for decontamination and/or disposal of PCBs	25
Table A.1 - List of PCBs manufacturers and commercial names	30
Table H.1- Equivalent toxicity (referred on 2,3,7,8 TCDD) and non-ortho and mono-ortho congeners concentration, and DIN congeners in commercial Aroclor PCB mixtures	
Table J.1 - Summary of PCBs Cleanup Levels required under US EPA Spill Policy	41

- 5 -

Introduction

Insulating liquids with PCBs bases (Askarels) or contaminated by PCBs that may still be present in electrical equipment in the generation, transmission, distribution and use of electric energy.

Polychlorinated biphenyls (PCBs) are a mixture of 209 possible congeners (as defined by EN 61619). Such compounds of a synthetic origin, have been produced and used in various commercial mixtures at an international level since 1930 (see Annex A). The chemical stability and relative non-flammable nature of PCBs was the main reason for their use by the electrotechnical industry.

The same functional features of these substances created environmental problems: PCBs are, in fact, classified as hazardous and persistent organic pollutants (POPs) in the environment, bio-accumulable along the food chain.

It is recognised that oil-filled electrical equipment may have been contaminated by PCBs either during manufacture or maintenance operations using oils which have been contaminated with PCBs.

Insulating liquids and equipment containing insulating liquids are classified, respectively, "PCBs" and "Equipment containing PCBs" when the total concentration of polychlorinated biphenyls (209 possible congeners) and correlated compounds PCTs (polychlorinated terphenyls-8 557 possible congeners) and PCBTs (polychlorinated benzyltoluenes-thousands of possible congeners) present in the insulating liquids exceeds the limits prescribed by current legislation for the single environmental matrices and/or applications (equipment and insulating liquids in operation, waste, used oils, fuel oils, etc.).

During their operational life cycle, such equipment and insulating liquids degrade, and may degrade faster if not properly managed and maintained, inducing failures that could cause incidents having a significant environmental impact, that can be correlated to the specific site conditions. In accordance with Directive 96/59/EC, during their service life, equipment containing PCBs should, under certain conditions, be subject to measures capable of preventing and/or mitigating degradation processes and the spillage of PCBs, to ensure the protection of workers, public health and the environment, as well as complying with the prescriptions of the Stockholm Convention on Persistent Organic Pollutants (POPs) entered into force on 17 May 2004.

Since the 1980's, PCBs have been subject to prohibitions and limitations for the marketing and use: the recent Council Directives and Commission Decisions introduced new obligations for the inventory, control, management, decontamination and/or disposal of electrical equipment and insulating liquid containing PCBs.

- 6 -

1 Scope

The scope of this Technical report is to provide guidance for the activities of inventory, control, management, decontamination and/or disposal of equipment and containers with insulating liquid containing PCBs, in compliance with the Council Directives (96/59/EC), using Best Available Techniques - BAT - (96/61/EC), Commission Decision (2001/68/EC), Stockholm Convention on Persistent Organic Pollutants (POPs) and/or with appropriate national or local legislation.

This Technical report is addressed, in particular, toward the Life Cycle Management (LCM) of insulating liquids and it has been developed in accordance with the following objectives:

- a) reduction of risks for workers, public health and the environment, arising from human error, malfunction, or failures of the equipment that could cause fires or spillage of hazardous and Persistent Organic Pollutants (POPS)s;
- b) implementation of the "Best Available Techniques" (BAT), "Best Environmental Practices" (BEP) and methodologies available for safety, whilst taking into account the surroundings and the criteria of self-sufficiency and functional recovery;
- c) technical feasibility of the activities within the prescribed time schedules, taking into account current legislation and economic feasibility.

NOTE 1 For those CENELEC countries in which the European Directives do not apply, this Technical report has an informative purpose only. Different limits from those given in the present Technical report are required in some countries.

NOTE 2 For those countries outside of European Community the Stockholm Convention on Persistent Organic Pollutants (POPs) should be applied.

NOTE 3 When reading this Technical report, reference should also be made to Annex C of EN 50195 and Annex B of EN 50225, because in some EU countries (i.e. France, Italy, Poland, Spain, etc.) there are other mandatory requirements.

2 Normative references

The following referenced documents may be used for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

EN 12766-1	Petroleum products and used oils - Determination of PCBs and related products - Part 1: Separation and determination of selected PCB congeners by gas chromatography (GC) using an electron capture detector (ECD)
EN 12766-2:2001	Petroleum products and used oils - Determination of PCBs and related products - Part 2: Calculation of polychlorinated biphenyl (PCB) content
EN 12766-3	Petroleum products and used oils - Determination of PCBs and related products - Part 3: Determination and quantification of polychlorinated terphenyls (PCT) and polychlorinated benzyl toluenes (PCBT) content by gas chromatography (GC) using an electron capture detector (ECD)
EN 50195	Code of practice for the safe use of fully enclosed askarel-filled electrical equipment
EN 50225	Code of practice for the safe use of fully enclosed oil-filled electrical equipment which may be contaminated with PCBs
EN 60567	Oil-filled electrical equipment - Sampling of gases and of oil for analysis of free and dissolved gases - Guidance (IEC 60567)
EN 60599	Mineral oil-impregnated electrical equipment in service - Guide to the interpretation of dissolved and free gases analysis (IEC 60599)
EN 61198	Mineral insulating oils - Methods for the determination of 2-furfural and related compounds (IEC 61198)



This is a free preview. Purchase the entire publication at the link below:

Product Page

S Looking for additional Standards? Visit Intertek Inform Infostore

> Learn about LexConnect, All Jurisdictions, Standards referenced in Australian legislation